



ORION TELECOM NETWORKS INC.

E1-PRI GSM-30 E1 PRI ISDN GSM Gateway with 30xGSM Interface(s) 30 SIMs per E1 Interface PRI ISDN Q.931 Signaling (EURO ISDN)

E1 PRI ISDN GSM Gateway - 30 SIM

Product Brochure & Data Sheet

Headquarters: Phoenix, Arizona

Orion Telecom Networks Inc.

20100, N 51st Ave, Suite B240,
Glendale AZ 85308

Phone: +1 480-816-8672

Fax: +1 480-816-0115

E-mail: sales@oriontelecom.com

Website: <http://www.oriontelecom.com>

Regional Office: Miami, Florida

Orion Telecom Networks Inc.

4000 Ponce de Leon Blvd. Suite 470,
Coral Gables, FL 33146 U.S.A.

Phone: 1-305-777-0419,

Fax: 1-305-777-0201

E-mail: sales@oriontelecom.com

Website: <http://www.oriontelecom.com>

Product Overview

The E1 PRI ISDN Q.931 (EURO ISDN) GSM Gateway with 30 SIMs (1 SIM per each GSM channel - 30 SIMs per E1). Integrates the E1 PRI ISDN interface to the GSM network to provide the user with 30, GSM links (1 SIM per channel) for mobile communications with an integrated E1 interface.

The E1 PRI ISDN GSM Gateway offers numerous applications for operators, which include terminating VoIP, VoATM, VoFR, VPN, DCME E1 traffic directly into the GSM network, connecting remote (distant) locations over GSM networks, providing rural connectivity over GSM networks, last mile connectivity over GSM networks, quick basic telephony provisioning, corporate business fixed to mobile/mobile to fixed, GSM connectivity for river boats, costal cruise ships, fixed network back-up via GSM, VPN connectivity between two corporate networks, mobile back-up solutions for corporate businesses with high security requirements, and many more applications.

The E1 PRI ISDN GSM gateway also replaces the cumbersome fixed wireless terminals and provides accurate answer supervision and line disconnect supervision, plus a host of other advantages, which include fast connection times (very short PDD) and high ASR rates that compete with the industry's best.

T1 GSM Channel Bank is also available.

The E1 PRI ISDN GSM Channel Banks/Gateways with the following features:

- The interface of the network side is E1 Digital Interface with PRI ISDN Q.931 (EURO ISDN) signaling
- The interface on the user side is up to 30 x GSM links (30 SIMs per E1-1 SIM per channel)
- Accurate answer supervision and disconnect supervision, from SS7 based GSM Networked signaling/GSM Switch
- Unique Caller ID blocking/Caller ID disabling feature (if network allows)
- Echo cancellation up to 128ms. provided - optional
- PRI ISDN (Euro ISDN) Q.931 signaling
- Remote access monitoring over TCP/IP network - optional
- All 30, GSM channels are dual band - 900MHz and 1800MHz with auto-sense/auto-switching capability
- Optional: All 30, GSM channels are dual band - 850MHz and 1900MHz with auto-sense/auto-switching capability.

Features and Highlights

- Compact, 30 GSM terminals (30 SIMs per E1) in a 19-inch chassis
- GSM is integrated to the E1 PRI ISDN Interface
- Exceptional voice quality. The two wire trans-hybrid analog path (present in the Fixed Wireless Terminals) is eliminated in the innovative design, resulting in improved voice quality, clearer voice and superior channel separation by reducing the susceptibility to echoes that result from the analog two wire trans-hybrid VF paths
- Provides accurate billing information ("answer supervision" and "line disconnect supervision") - not provided by Fixed Wireless Terminals
- Integrated, optional, E1 Echo-Canceller to cancel echo tails from inherent delays of VoIP/VoFR networks - 64ms. Unidirectional, 128ms. Unidirectional and 64ms. Bidirectional options available.
- Lower cost - resulting from complete, GSM to E1 integration
- Plug-And-Play
- Easy to install
- Takes only minutes to install and start service.

Advantage over fixed wireless Terminals Solutions

Integrated E1 GSM Channel Bank - PROS	Third Party component solutions comprising of E1 Channel Banks and 30 (E1) Fixed Wireless Terminals - CONS
1. Integrated and Compact 30, (E1) GSM channels in a compact 6U high, 19-inch rack-mountable shelf.	1. Discreet and poorly managed solution comprising of a channel bank and discreet and 30 (E1) Fixed Wireless Terminals.
2. Integrated, Single Power Input: -48V DC or AC Mains. Both options are provided.	2. Individual 30 (E1) Fixed Wireless Terminals with 30, separate power inputs. Difficult to manage.
3. 3.5dB gain, external antennas with 2 meter RG174 cable and antenna trays. Easy to manage.	3. Absence of External Antennas provides no additional signal gain.
4. Offers Remote and Integrated Graphical User Interface (GUI) Management to monitor all GSM channels. This option allows the USER to view and monitor the status of ALL 30 GSM channels, including FAULTS on any of the individual GSM channels, remotely, over a TCP-IP network.	4. No management facility to monitor the GSM terminals remotely, or to view the channel or fault status on any of the GSM channels.
5. Integrated, 64ms. and 128ms. Echo Canceller option. This option allows the USER to install a 64ms./128ms. Echo Canceller in the same 19-inch chassis, to effectively remove any echoes resulting from VoIP and VoFR network delays.	5. No option of ANY Echo Canceller, which are often essential and required in VoIP and VoFR call termination, owing to unacceptable echoes which often result from network delays.
6. Direct E1-A Law to GSM Conversion to GSM conversion, with patented (patent pending) noise reduction technology. Greatly improves voice quality and voice clarity.	6. Poor coupling of analog lines (from the E1 channel banks) to GSM Fixed Wireless Terminals often results in the analog lines picking up a lot of GSM transmission noise often resulting in unacceptable voice quality and poor quality service.

Advantage over fixed wireless Terminals Solutions

Integrated E1 GSM Channel Bank - PROS	Third Party component solutions comprising of E1 Channel Banks and 30 (E1) Fixed Wireless Terminals - CONS
<p>7. Greater product reliability. Integration results in greater product reliability and results in less downtime resulting from a low failure rate.</p>	<p>7. Poor product reliability resulting from low integration, poor management and a high number of individual components that are required to be managed 30 individuals Fixed Wireless Terminals, each with separate power supplies, and the channel bank.</p>
<p>8. Accurate CALL METERING resulting from accurate answer-supervision and line-disconnect supervision since the integrated E1, GSM Channel Bank derives its answer-supervision (required for the call-metering function), from the SS7 based GSM Network Signaling/GSM Switch.</p>	<p>8. Unreliable CALL METERING resulting from a battery reversal based, or VAD based (Voice Activated) answer supervision, which is based on analog technology and prone to errors. A VAD based answer supervision offers unreliable CALL METERING, in comparison with the integrated E1, GSM Channel Bank which derives its answer-supervision (required for the call-metering function), from the SS7 based GSM Network Signaling/GSM Switch.</p>
<p>9. Low Cost. Integration also results in cost reduction when compared with a component based, discreet solution comprising of an E1 Channel Bank PLUS 30 Fixed Wireless Terminals.</p>	<p>9. Higher cost. The cost appears to be even higher, the absence of any available features, and in case of poor product management, poor product integration resulting in lower product reliability is taken into consideration.</p>

Technical Specifications

Digital Interface 2048 Kbps

Number of E1, PRI ISDN interfaces	1 - (User or Network Modes - Configurable)
Conformity (Electrical)	G. 703
Frame Structure	As per ITU (CCITT) G.704
Signaling	PRI ISDN (Euro ISDN) signaling as per ITU-T Rec. Q.921, Q.931
PCM Sampling Rate	8000 samples/sec
Encoding Law	A Law as per ITU (CCITT) G.823
Bit Rate	2048 Kbps \pm 50 ppm
Code	HDB3
Nominal impedance	120 Ω balanced
Connector Type	RJ-45
Pulse Mask	As per ITU (CCITT) Rec. G.703
Output Jitter	<0.05 UI (in the frequency range of 20Hz -100 KHz)
Permissible Attenuation	6dB at 1 MHz
Return Loss at: 51.2 KHz to 102.4 KHz 102.4 KHz to 2048 KHz 2048 KHz to 3072 KHz	>12dB >18dB >14dB
Jitter Tolerance	As per ITU (CCITT) G.823
Loss and recovery of frame alignment	As per clause 3 of ITU (CCITT) G.732
Loss and recovery of multi frame Alignment	As per clause 5.2 of ITU (CCITT) G.732

Power Supply Card

Input DC voltage	- 48V DC (nominal)
Range of input	- 40V to - 60V DC
Output voltages	+5V
Full Load Output Current	18A@5V DC
Input Voltage Reversal Protection	Provided in the Card
Over Current Protection	20A for +5V
Short Circuit Protection	Current limit - 20A. Recovers on removal of short
Under Voltage	< 4.5V
Over Voltage	5.4V to 5.6V
Efficiency at full load	>80%
Ripple at full load	<5mVrms
Spike at full load	<50mV
Power Consumption	120 Watts (Worst Case)

GSM Access Card

Number of GSM Interfaces	1 ~ 30 (Stackable, 1 thru 30).
Number of SIM Cards per GSM Interface	1 SIM per GSM Channel 30 SIMs per E1
Type	Dual Band EGSM 900 MHz and EGSM 1800 MHz Optional Dual Band 850 MHz - 1900 MHz
Compliance	Compliant with ETSI GSM Phase 2+ standard (Normal MS) Class 4 (2W @ 900MHz) Class 1 (1W @ 1800 MHz)
Approvals	Fully Type Approved to GSM Standards
SIM Interface Internal Tray	Toolkit Class 2. 3V Reader
Voice Features	Full Rate, Enhanced Full Rate and Half-Rate (FR/EFR/HR and AMR)
Caller ID	Enable/Disable-User Selectable

Connectorized Antenna Cable

Electrical Properties

Parameter	Description
Frequency Band	900~1800 MHz
Nominal Impedance	50 Ohms
V.S.W.R	<1.8
Antenna Average Gain	2.5 dBi

Mechanical Properties

Parameter	Description
Antenna Type	Mini Mag Antenna
Cable Cover	Black
Antenna Cable	RG174U
Antenna Color	Black
Cable OD	Ø 2.6 ± 0.1 mm
Operating Temperature Range	- 40°C~+85°C

Approvals

Regulatory: R&TTE directive, GCF-CC, CE marking, FCC, PTCRB
• Manufacturing: ISO TS 16949
• Quality: ISO 9001

The modules are approved worldwide under test standards including:

• Radio and Telecommunication Terminal Equipment (R&TTE)
• Global Certification Forum
• Certification Criteria (GCF-CC)
• EMC, Safety.

Alarms

An alarm shall be displayed in LED L1/L2 for the following reasons:

- Invalid SIM Card
- Unregistered SIM Card
- Faulty SIM Card
- GSM Access Card Out of Range

Echo Canceller Cards

- Provides voice echo cancellation of up to 64ms/128ms (Bidirectional) or 128ms (Unidirectional) Echo Cancellation
- Conforms to ITU-T G.165 and ITU-T G.168
- G.164/G.165 disable tone detection
- Non-Linear Processor with Comfort Noise Insertion
- Narrow-Band Detector
- Eliminates long echo tail.

Mechanical Specifications

Rack Mounting	Standard 19-Inch DIN Rack
Height	6U (265 mm)
Depth	290 mm
Width	19-inch (477mm)
Weight	12Kgs. (Net)

E1 Echo Canceller - E1 Interface (Optional)

Number of Interfaces	1, 1 - Input, 1 - Output
Conformity	G.703
Frame Structure	As per ITU (CCITT) G.704
Signaling	Pass-Through
PCM Sampling Rate	8000 Samples / sec
Encoding Law	ALaw as per ITU (CCITT) G.711
Bit Rate	2048 Kbps \pm 50 ppm
Code	HDB3
Nominal Impedance	120 Ω balanced
Peak Voltage of a mark For 120 Ω Balanced interface	3.0 V \pm 0.3 V
Peak Voltage of a space For 120 Ω balanced interface	0 V \pm 0.3 V
Nominal Pulse Width	244 ns
Pulse Mask	As per ITU (CCITT) Rec. G.703
Output Jitter	< 0.05 UI (in the frequency range of 20Hz to 100 KHz)
Permissible Attenuation	6 dB at 1 MHz
Return Loss at: 51.2 KHz to 102.4 KHz 102.4 KHz to 2048 KHz 2048 KHz to 3072 KHz	> 12dB > 18dB > 14dB
Jitter Tolerance	As per ITU (CCITT) G.823
Loss and recovery of frame alignment	As per clause 3 of ITU (CCITT) G.732
Loss and recovery of multiframe alignment	As per clause 5.2 of ITU (CCITT) G.732

Ordering Information

S.No.	Part No.	Product Description	Qty
1.	E1-015-PRI	Control Card, E1 PRI ISDN Interface Card	01
2.	E1-000/005-PRI	19" Shelf 3U High (Sub-rack) to accommodate 30 GSM Channels with Connectorized Backplane 6U High	01
3.	E1-010	(-) 48V DC Power Supply Card	02
4.	E1-030-PRI	Dual Port GSM Interface Card - GSM terminals connect to an E1 Interface, 15 Cards (max) per system	15 (max.)
5.	E1-030-ANT	External Antennas with 2 meters Connectorized Cable	30
6.	E1-150W	Power Supply (External) AC to DC Converter Portable External Converter Universal AC Input [93V AC-276V AC, 47Hz-63Hz] to DC Output [(-) 48V DC]	01

Common Equipment

Optional

7.	E1-EC64-U	E1 Echo Canceller Card, provides 64ms of unidirectional echo cancellation. One Card required for every E1-GSM Shelf	01
8.	E1-EC128-U	OR E1 Echo Canceller Card provides 128ms of unidirectional echo cancellation. One Card required for every E1-GSM Shelf	01

Optional

9.	E1-TCP-IP	TCP-IP remote access for configuration Option allows the user to access, configure and control the E1-GSM/E1 Channel Bank equipment over a TCP-IP network. One required for every E1-GSM Shelf	01
----	-----------	--	----

Notes : _____

Technical specifications are subject to changes without notice.
All brand names and trademarks are the property of their respective owners.
Revision 04 - December 20, 2006

Headquarters: Phoenix, Arizona

Orion Telecom Networks Inc.

20100, N 51st Ave, Suite B240,
Glendale AZ 85308

Phone: +1 480-816-8672

Fax: +1 480-816-0115

E-mail: sales@oriontelecom.com

Website: http://www.oriontelecom.com

Regional Office: Miami, Florida

Orion Telecom Networks Inc.

4000 Ponce de Leon Blvd. Suite 470,
Coral Gables, FL 33146 U.S.A.

Phone: 1-305-777-0419,

Fax: 1-305-777-0201

E-mail: sales@oriontelecom.com

Website: http://www.oriontelecom.com